

CLUB ICOM 7300 Mk2 - FLDIGI

FLDIGI

PRE-SET 3 FLDIGI

Name	fldigi
Mode	USB-D
Filter	FL1
Filter BW	2.6 kh
Filter Type	Sharp
USB O/P Select	AF
USB AF Level	50%
USB Sql	Off
USB Mod Level	50%
Data Mod	USB
SSB-D Tx BW	120 – 2500
Data Off Mod	Mic
Comp	Off
USB Send	USB (A) RTS
USB Key (CW)	Off
USB Key (RTTY)	Off
CI-V Baud Rate	19200
CI-V Addr	94h
CI-V Transceive	On
CI-V Echo Back	Off

FLDIGI (Program dialog)

COM ?	As Defined by Windows
Hamlib Rig	Icom 7300 (Stable)
Hamlib Device	Com ?
Baud rate	19200
PTT	via Hamlib
Side Band	Rig mode
CW	LSB
RTTY	USB
Sound Card Devices	Port Audio Capture Mic (USB Audio) Play Back Speakers (USB Audio)
Right Channel	Modem Signal Right and Left