

CLUB ICOM 7300 Mk2 - FT8

FLDIGI

PRE-SET 2 FT8

Name	FT8
Mode	USB-D
Filter	FL1
Filter BW	2.9 kh
Filter Type	Sharp
USB O/P Select	AF
USB AF Level	60%
USB Sql	Off
USB Mod Level	50%
Data Mod	USB
SSB-D Tx BW	120 – 2900
Data Off Mod	Mic
Comp	Off
USB Send	USB (A) RTS
USB Key (CW)	Off
USB Key (RTTY)	Off
CI-V Baud Rate	19200
CI-V Addr	94h
CI-V Transceive	On
CI-V Echo Back	Off

FOR THE MK1 The above settings and -

USB Serial Function	CI-V
CI-V USB Port	Unlink from Remote

Note You must have installed the ICOM USB Drivers on your Computer

FT8 (SETTINGS)

RADIO	
COM ?	As Defined by Windows
RADIO	Icom 7300 (Stable)
BIT	64
Baud rate	19200
PTT Method	RTS
PORT(COM)	AS DEFINED BY WINDOWS (SAME AS ABOVE)
DATA/PKT	
FAKE IT	
AUDIO	
	Input Mic (USB Audio Codec)
	Out Put Speakers (USB Audio Codec)
Refresh	
OK	