

ICOM 7300 MK2 - N1MM DATA FLDIGI EMBEDDED

Preset (5)

Name	N1MM Data - 2 port
Mode	USB – D
Filter	F1
Filter BW	2.7k
Filter Type	Sharp
USB o/p Select	AF
USB AF o/p Level	50%
USB AF Sql	Off
USB Mod Level	50%
Data Mod	USB
SSB – D Tx BW	150 – 2700
Data Mod Off	Mic
Comp	Off
USB Send	USB (B) RTS
USB Key (CW)	Off
USB Key (RTTY)	Off
CI-V Baud Rate	19200
CI-V Addr	B6h
CI-V Transceive	On
CI-V Echo Back	Off

N1MM

Load Digital Log

Config

COM ?	COM A (C1-V)	As Defined by Windows
IC 7300MK2	CW Other	
Set	19200 Baud	
DTR	Off	
RTS	Off	
Icom Mode	B6h	
Ptt Delay	25mSec	
COM ?	COM B	As Defined by Windows
RADIO	NONE	CW OTHER
SET	DTR Off,	PTT On

Window

Digital Interface

Fldigi

Config

Sound Card Devices – Port Audio

Capture Mic (USB Audio)

Play Back Speakers (USB Audio)

Right Channel Modem Signal Right and Left